



AMD Proprietary Linux Release Notes

This release note provides information on the latest posting of AMD's Proprietary Linux driver. This particular driver updates the software version to 8.65.

The AMD Linux release notes provide information on the following:

- *Web Content*
- *ATI Workstation Product Support*
- *ATI Mobility™ and Integrated Mobility™ Product Family Support*
- *ATI Desktop Product Family Support*
- *ATI Integrated Product Family Support*
- *AMD FireStream™ Product Family Support*
- *Operating Systems Distributions Supported*
- *System Requirements*
- *New Features*
- *Resolved Issues*
- *Known Issues*
- *Installing the AMD Proprietary Linux Software Driver*
- *Driver Update Notification*
- *Linux Feedback Program*

Web Content

The ATI Catalyst™ Linux Graphics Driver software suite is available through an installer executable.



Note: Refer to the minimum system requirements listed below to ensure you have downloaded the correct driver package for your system.

ATI Workstation Product Support

The ATI Catalyst™ Linux software suite is designed to support the following ATI Workstation products:

AMD Workstation Family Product Support	
ATI FirePro™ V8750	ATI FirePro™ 2260
ATI FirePro™ V8700	ATI FireGL™ V8650
ATI FirePro™ V7750	ATI FireGL™ V8600
ATI FirePro™ V5700	ATI FireGL™ V7700
ATI FirePro™ V3750	ATI FireGL™ V7600
ATI FirePro™ V3700	ATI FireGL™ V5600
ATI FirePro™ 2450	ATI FireGL™ V3600

ATI Mobility™ and Integrated Mobility™ Product Family Support

The ATI Catalyst™ Linux software suite is designed to support the following ATI Mobility™ products:

AMD Mobility™ Product Family Support	
ATI Mobility Radeon™ HD 4870	ATI Mobility Radeon™ HD 4100
ATI Mobility Radeon™ HD 4860	ATI Mobility Radeon™ HD 3870
ATI Mobility Radeon™ HD 4850	ATI Mobility Radeon™ HD 3850
ATI Mobility Radeon™ HD 4830	ATI Mobility Radeon™ HD 3670
ATI Mobility Radeon™ HD 4670	ATI Mobility Radeon™ HD 3650
ATI Mobility Radeon™ HD 4650	ATI Mobility Radeon™ HD 3430
ATI Mobility Radeon™ HD 4500	ATI Mobility Radeon™ HD 3400
ATI Mobility Radeon™ HD 4300	ATI Mobility Radeon™ HD 2600
ATI Mobility Radeon™ HD 4200	ATI Mobility Radeon™ HD 2400

ATI Desktop Product Family Support

The ATI Catalyst™ Linux software suite is designed to support the following ATI desktop products:

AMD Desktop Product Family Support	
ATI Radeon™ HD 4890 Series	ATI Radeon™ HD 4550 Series
ATI Radeon™ HD 4870 X2 Series	ATI Radeon™ HD 4350 Series
ATI Radeon™ HD 4850 X2 Series	ATI Radeon™ HD 3800 Series
ATI Radeon™ HD 4800 Series	ATI Radeon™ HD 3600 Series

ATI Radeon™ HD 4700 Series	ATI Radeon™ HD 3400 Series
ATI Radeon™ HD 4670 Series	ATI Radeon™ HD 2900 Series
ATI Radeon™ HD 4650 Series	ATI Radeon™ HD 2600 Series
ATI Radeon™ HD 4600 Series	ATI Radeon™ HD 2400 Series



Note: The ATI Radeon™ HD 3870 X2 series of product is currently not supported by the ATI Catalyst™ Linux software suite.



Note: All-in-Wonder™ variants based on the above are also supported. However, video capture is not supported.



Note: Software driver support for ATI FireGL™, Integrated, Mobility™ and Desktop products prior to the Radeon™ 9500 is available from www.amd.com.

ATI Integrated Product Family Support

The ATI Catalyst™ Linux software suite is designed to support the following **ATI** desktop products:

AMD Chipset Product Support	
ATI Radeon™ HD 4200 Series	ATI Radeon™ 3100 Series
ATI Radeon™ HD 3300 Series	ATI Radeon™ 3000 Series
ATI Radeon™ HD 3200 Series	

AMD FireStream™ Product Family Support

The ATI Catalyst™ Linux software suite is designed to support the following **AMD** products:

AMD FireStream™ Product Support	
AMD FireStream™ 9270	AMD FireStream™ 9170
AMD FireStream™ 9250	

Operating Systems Distributions Supported

The latest version of the ATI Catalyst™ Linux software suite is designed to support the following Linux distributions:

-
- Red Hat Enterprise Linux suite
 - Novell/SuSE product suite
 - Ubuntu



Note: The ATI Catalyst™ Linux software suite may install on a number of other Linux distributions. Refer to the Package Generation installation instructions for more information.



Note: AMD has contributed packaging scripts to allow creation of other packages, but does not necessarily test, verify or warrant the reliability. Currently Red Hat Enterprise Linux suite and Novell/SuSE product suite are supported Linux distributions.

System Requirements

Before attempting to install the ATI Catalyst™ Linux software suite, the following software must be installed:

- XOrg 6.8, 6.9, 7.0, 7.1, 7.2, 7.3 or 7.4
- Linux kernel 2.6 or above
- glibc version 2.2 or 2.3
- POSIX Shared Memory (/dev/shm) support is required for 3D applications

The ATI Catalyst™ Linux software suite no longer provides precompiled Kernel Modules; all installations require GCC compiler and kernel-headers or kernel-source in order to enable 2D and 3D acceleration.

For best performance and ease of use, ATI recommends the following:

- Kernel module build environment
 - Kernel source code include either the Kernel Source or Kernel Headers packages
- The RPM utility should be installed and configured correctly on your system, if you intend to install via RPM packages

The following packages must be installed in order for the Catalyst™ Linux driver to install and work properly:

- XFree86-Mesa-libGL
- libstdc++
- libgcc
- XFree86-libs
- fontconfig
- freetype
- zlib
- gcc

New Features

This section provides information on new features found in this release of the Radeon™ Display Driver. These include the following:

- *Support for New Linux Operating Systems*

Support for New Linux Operating Systems

This release of ATI Catalyst™ Linux introduces support for the following new operating system:

- OpenSUSE 11.1 production support
- SLED and SLES 10 SP3 early look support

Resolved Issues

The following section provides a brief description of resolved issues with the latest version of the ATI Catalyst™ Linux software suite. These include:

- [RandR 1.2] Enabling a disabled GPU no longer causes desktop overlap (default monitor section not being used)
- Catalyst Control Center: The refresh rate is now preserved after restarting X
- [SuSE 11.0] With desktop effects enabled, system no longer fails when switching to another Virtual Terminal
- Catalyst Control Center: The "Identify" icon now rotates when screen is rotated with RandR 1.2
- The "Identify" icon no longer disappears after resolution change
- "Force maximum performance clocks " status in Catalyst Control Center now functions properly when change is applied to a single adapter for specific ASICs
- With CrossFire enabled, Catalyst Control Center no longer throws segmentation fault while selecting the secondary display
- CrossFireX settings in Catalyst Control Center now reflect when CrossFire is enabled/disabled properly
- [Ubuntu 9.04] Under specific system configurations, resume from S3 and S4 in extended desktop mode no longer causes the desktop to appear with no menu or icons
- Hotplugging the second display no longer causes X to fail with the keyboard and mouse becoming inoperable
- Bringing up the Catalyst Control Center display selector in the CrossFire Diagnostic aspect no longer causes X to fail on specific ASICs

Known Issues

The following section provides a brief description of known issues associated with the latest version of ATI Catalyst™ Linux software suite. These issues include:

- Some CAL SDK samples throws an error message while executing on the second ASIC

-
- `aticonfig -xinerama=on` may result in different dimensions and DPI settings between Ubuntu 8.10 and 9.04
 - Display corruption may be observed after changing TV format from NTSC to PAL and restarting X server
 - System may become unresponsive after executing specific combinations of Xrandr reflections and rotations
 - X server may fail to start GUI Desktop Manager after enabling secondary adapter using Catalyst Control Center
 - [Ubuntu 9.04] Animated busy mouse cursor may disappear or flicker in Clone mode
 - Corruption may be visible after hotplugging a display and doing a Virtual Terminal switch
 - Changes to gamma values may be applied to the wrong display when X is restarted
 - Systems with both CRT and LVDS displays connected may fail to respond when starting the X server on some ASICs
 - Segmentation fault may occur or system may display error during boot up if X is stopped in Dual-Head mode



Note: On Novell's openSUSE, SLED and SLES operating systems running “sax2” or “sax2 -r” on the console overwrites the X.Org configuration file `xorg.conf`, reverting changes made by running “`aticonfig --initial`”. As a result subsequent X session may start up using the open source Radeon on X-Vesa graphics drivers instead of the proprietary ATI Linux Graphics Driver.

Solution: Do not use Sax2 when the proprietary Linux Graphics Driver is installed. Instead configure all display parameters using the Catalyst Control Center--Linux Edition or the `aticonfig` command line interface.

Installing the AMD Proprietary Linux Software Driver

Installation information can be found at: [How to Install Your ATI Product](#).

Driver Update Notification

To receive driver notifications, add the following RSS feed to your RSS reader:
<http://www2.ati.com/rss/catalyst.rss>



Note: In order to receive notifications you will need to have an RSS reader installed.

Linux Feedback Program

The ATI Catalyst™ Linux software suite releases may incorporate suggestions received through the Linux feedback program.

Please refer to <http://www.amd.com/us/LinuxCrewSurvey> to provide us with feedback.